

# ATEM Production Studio 4K



ATEM Production Studio 4K lets you connect up to 8 SD, HD or Ultra HD 4K video cameras, disk recorders and computers to do true broadcast quality work. You get all the features you expect from a professional switcher including chroma key, transitions, media pool, downstream keyers, audio mixer, multi view and the world's first 6G-SDI and HDMI 4K video connections.

**\$1,695**

## Connections

### Total Video Inputs

8

### Total Video Outputs

6

### SDI Rates

270Mb, 1.5G, 3G, 6G.

### Total Audio Inputs

2 x XLR. 2 x RCA.

### Total Audio Outputs

2 x XLR Program.

### Timecode Connection

None

### SDI Video Inputs

4 x 10-bit SD/HD/Ultra HD 4K switchable. 2 channel embedded audio.

### HDMI Video Inputs

4 x HDMI type A, 10-bit SD/HD/Ultra HD 4K switchable. 2 channel embedded audio.

### SDI Audio Outputs

2 channel embedded into SDI output.

### Reference Input

Tri-Sync or Black Burst.

### Video Input Re-Sync

On all 8 inputs.

### SDI Program Outputs

1 x 10-bit SD/HD/Ultra HD 4K switchable.

### HDMI Program Outputs

1 x HDMI type A, 10-bit SD/HD/Ultra HD 4K switchable.

### Down Converted SDI

#### Program Outputs

1 x 10-bit HD (Ultra HD 4K to HD).

#### SDI Aux. Output

1

#### Total Multi Views

1

#### SDI Multi View Outputs


1

#### HDMI Multi View Outputs

1

### Control Panel Connection

Ethernet supports 10/100/1000 BaseT. Allows direct connection between panel and chassis, or via network.



<b>Color Generators</b> 2	<b>Display interface</b> Minimum monitor resolution of 1366 x 768.	<b>Tally</b> Red for program and green for preview indication.
<b>DVE with 3D Borders &amp; Drop Shadow</b> None	<b>Number of Windows</b> 1 x 10	<b>Windows Source Labels</b> Yes
	<b>Routable Windows</b> 8	<b>Control Panel</b> Software or optional hardware panel.

## Media Player

<b>Media Players</b> 2	<b>Media Player Clip Length in 1080 HD</b> None	<b>Media Pool Audio File Format</b> None.
<b>Media Pool Still Image Capacity</b> 20 with fill and key.	<b>Media Player Clip Length in Ultra HD</b> None	<b>Channels</b> Fill and key for each Media Player.
<b>Media Pool Clip Capacity</b> None	<b>Media Pool Still Image Format</b> PNG, TGA, BMP, GIF, JPEG and TIFF.	
<b>Media Player Clip Length in 720 HD</b> None	<b>Media Pool Video File Format</b> None.	

## Multi View Monitoring

<b>Multi View Monitoring</b> 1 x 10 Views.	<b>Multi View Video Standard</b> HD.
---	---

## Display


<b>Interface</b> Minimum monitor resolution of 1366 x 768.	<b>Front Panel</b> Built in LCD monitor for video and 42 LED buttons for Aux switching.
---	--

## Software

<b>Control Panel Included</b> ATEM Software Control Panel included free for Mac 10.10 Yosemite, Mac 10.11 El Capitan or later and Windows 8.1 64-bit or Windows 10 64-bit.	<b>Tally Output</b> Added via Ethernet connection to Blackmagic Design GPI and Tally Interface product. (Not included.)  <b>Software Updates</b> Using USB connection directly connected to Mac or Windows computers. Includes ATEM Setup Utility	<b>Configuration</b> Set via ATEM Software Control Panel, excluding ATEM chassis IP address which is set via the ATEM Setup Utility connected via USB to chassis.
---	---	--

---

## Operating Systems



Mac 10.14 Mojave,  
Mac 10.15 Catalina or later.



Windows 8.1 and 10.

---

## Power Requirements

### Power Supply


1 x Internal 100 - 240V AC.

### Power Usage

60W

---

## Physical Specifications



---

## Environmental Specifications

### Operating Temperature

0° to 40° C (32° to 104° F)

### Storage Temperature

-20° to 60° C (-4° to 140° F)

### Relative Humidity

0% to 95% non-condensing

---

## What's Included

ATEM Production Studio 4K  
SD card with software and manual

---

## Warranty

12 Month Limited Manufacturer's Warranty.

### Repair policy

Warranty details can be found in the ATEM Switchers Operation Manual in the support page at [www.blackmagicdesign.com](http://www.blackmagicdesign.com)

Blackmagic Design Authorized Reseller