ATEM 4 M/E ADVANCED PANEL

This massive model is big enough to perfectly match the features on the ATEM Constellation switcher! It features 4 M/E rows with 40 input buttons per row and 4 independent system control LCDs for each row. This massive panel includes 24 LCD's for custom labeling of every button on every row!



Cena:
Kategorie: Video, Produkcja, Miksery wizyjne, Broadcast, Miksery wizyjne

OPIS

Connections

Ethernet

4 x 10/100/1000 BaseT with loop output for additional control panels or computers.

Software Updates

1 x USB-C for firmware updates.

Product Specifics

Number of Mix Effects Rows

4

Direct Cross Points

40

Shifted Cross Points

80

Crosspoint Button Type

Tri-Color LED

Crosspoint Label

10 rows 24 character LCD

Next Transition Selectors

4 x BKG, Key 1 - Key 4.

On-Air indicator

20

Power Status Indicators

None

DSK Transition Selectors

Auto, Cut, Tie/Preview x 4

Preview Transition

4

Transition Rate Displays

Via main menu

LCD Menu Displays

4

Menu Control

20 buttons x 4

Dedicated Macro Buttons

4 x 40

Transport Control Buttons

24

Destination Bus

4

Source Select Bus

4

Fader Bar

4

3 Axis Joystick

1

Numeric Keypad

1

Software

Software Applications

ATEM Software Control Panel.

Operating Systems

Mac 10.14 Mojave,
Mac 10.15 Catalina or later.
Windows 10, 64-bit.

Power Requirements

Input Voltage

2 x Internal 100 - 240V AC.

Redundant Power

Yes

Power Usage

250W

Physical Specifications

Environmental Specifications

Operating Temperature

0° to 40° C (32° to 104° F)

Storage Temperature

-20° to 60° C (-4° to 140° F)

Relative Humidity

Up to 95%

What's Included

ATEM 4 M/E Advanced Panel

Warranty

12 Month Limited Manufacturer's Warranty.